

SPECIFICATION

2L886754991US

5

TITLE:

Multimode Operation of Quadrature
Phased Array MR Coil Systems

10

INVENTOR:

George J. Mistic, Allison Park, Pa.

ASSIGNEE:

Medrad Inc., Indianola, Pa.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2

MULTIMODE OPERATION OF QUADRATURE PHASED ARRAY MR COIL SYSTEMS

5

CROSS-REFERENCE TO RELATED APPLICATION

This application claims the benefit of U.S. Provisional Application No. 60/109,820, filed November 25, 1998.

10

BACKGROUND OF THE INVENTION

The advantages of using phased array or multi-coil MR coil systems to enhance magnetic resonance imaging and spectroscopy are well known. A situation facing the designer of such coils is the finite number of available simultaneous data acquisition channels in the host MR system; frequently, there are only four available channels, sometimes known as receivers, in the host system.

Another issue is the reconstruction time to create the images from the collected data; processing multiple channels to form a single image increases the time needed by the magnetic resonance imaging system to process the data, by two or three dimensional Fourier Transform techniques or other methods, to create the final images. Another consideration is the fact that data acquisition hardware with additional performance capabilities may only be available on one receiver, or on fewer than the total number of available receivers.

SUMMARY OF THE INVENTION

Reconstruction of an image from two quadrature modes of a specific phased array coil element via two separate data acquisition channels [or receivers] provides the best possible image signal to noise ratio and uniformity, since the data can always be reconstructed in the most optimum way. However, the use of two separate receivers for the two quadrature signals from a specific phased array coil element may cause problems with reconstruction time, or limitations due to the finite number of available receivers. Thus, there may be conditions when combining the two quadrature signals at the RF level into a single signal may be most advantageous, and other times when processing the two RF signals independently via two separate data acquisition receivers may be the best scheme.

The present invention allows the two quadrature signals to be acquired as a single signal, precombined at the RF level within the coil interface, or as two separate RF signals by two of the receivers of the phased array hardware. It also provides a means for remote selection of the mode of operation from the operator's console when the system is used with a MRI system, such as the GEMS Signa system.

BRIEF DESCRIPTION OF THE DRAWINGS

The preferred embodiments of the present invention are illustrated by way of example, and not limitation, in the figures of the accompanying drawings, in which:

Figure 1 is wire model of a phased array neurovascular coil;

5 Figures 2A and 2B are electrical schematics of a coil interface circuit that provides multimode operation of the phased array neurovascular coil shown in Figure 1;

Figure 3 is a wire model of the phased array neurovascular coil in a first operational mode;

10 Figure 4 is a wire model of the phased array neurovascular coil in a second operational mode; and

Figure 5 is a wire model of the phased array neurovascular coil in a third operational mode.

DETAILED DESCRIPTION OF THE PRESENTLY PREFERRED EMBODIMENT(S) OF THE INVENTION

The presently preferred embodiments of the invention will now be described with reference to the Figures, in which like elements are referred to by like numerals. A number of specific applications of a preferred embodiment are discussed. In particular, the multimode operation of a neurovascular coil designed for and operating on the General Electric Medical Systems Signa MRI system is described; however, the preferred embodiments may be applied to other coils and other systems by those skilled in the art after reviewing this detailed description.

Figure 1 is wire model of a phased array neurovascular coil 50, also referred to herein as a neurovascular array coil. The neurovascular array coil 50 contains four separate imaging coils. The first coil is a quadrature tapered birdcage 60 covering the brain and head. Further details regarding the quadrature tapered birdcage are provided in U.S. Application No. _____, atty ref. no. 99,443-A, filed November 24, 1999, the contents of which are incorporated herein by reference. The first coil may alternatively be in the form of a domed birdcage, such as is described in US Patent No. 5,602,479, the contents of which are incorporated herein by reference, although the tapered birdcage is preferred because it provides improved field homogeneity on the XZ and YZ image planes.

The second coil is formed from two posterior cervical spine coils 70, the outputs of which are preferably combined at the RF level. The third and fourth coils are a superior anterior neck coil 80 and an inferior anterior neck coil 90. In accordance with an alternative embodiment, the outputs of the two posterior cervical spine coils 70 are not combined at the RF level and a single anterior neck coil (not shown) replaces the neck coils 80 and 90.

In accordance with a preferred embodiment, the superior anterior neck coil 80 and the inferior anterior neck coil 90 are mounted in an adjustable manner. For example, referring to Figure 1, the neck coils 80 and 90 may be housed in a support structure 85, as is known to those skilled in the art. In a preferred embodiment, the support structure 85 is mounted in a hinged manner, with the hinge location being toward the superior end of the support structure 85. When mounted in this manner, the inferior end of the support structure 85 may be raised and/or lowered, depending upon the size of the test subject, and may rest on the chest area of the test subject. This provides the advantage of locating the neck coils 80 and 90 as close to the test

subject as possible, thereby improving image quality over embodiments in which the neck coils 80 and 90 are fixedly located.

Figures 2A and 2B are electrical schematics of a coil interface circuit 100 that provides multimode operation of the phased array neurovascular coil 50 shown in Figure 1. The coil interface circuit 100 couples the phased array neurovascular coil 50 to a magnetic resonance imaging system. The coil interface circuit 100 has a number of signal input points 102, which are coupled to receive MR signals from the phased array neurovascular coil 50. As shown in Figure 2A, signal inputs 102 are coupled to output ports, port #2, port #3, port #4, port #5, and port #6, which are in turn coupled to predetermined MRI system receivers. Many systems, including the GEMS Signa system, provide only four receiver channels. Thus, because all the signal inputs 102 cannot simultaneously be applied to the MRI system receivers when the number of potential signal inputs 102 exceeds the number of receivers, the interface circuit 100 allows selected signal inputs 102 to be coupled to the MRI system receivers.

Selection of the operational modes of the phased array neurovascular coil 50 is made in the coil interface 100 unit by the use of PIN diode RF switches, as further described below. The following table defines the relationship between signal inputs 102 to the coil interface 100 and outputs, e.g. port #2-6, from the coil interface 100.

Signal	SMB	System Port	System Receiver
Head I	P4	5	0
Head Q (high res)	P5	6	1
Head Q (high speed)	P5	5	0
Cspine	P7	4	3
ANT SUP	P6	3	2
ANT INF	P8	2	1

In the table above, Head I refers to the in-phase MR signal from the birdcage coil 60, Head Q refers to the quadrature MR signal from the birdcage coil 60, Cspine refers to the combined MR signals from the posterior cervical spine coils 70, ANT SUP refers to the MR signal from the superior anterior neck coil 80, and ANT INF refers to the MR signal from the inferior anterior neck coil 90.

As shown in Figure 2A, the coil interface 100 is coupled to DC power supplies, +15V and -15V, from the MRI system. The electrical schematic of Figure 2A also includes a number of inductors, labeled as "RFC"s, that function as RF chokes. The RF chokes are preferably self-resonant at approximately 63.87 MHz. For example, the RF chokes may be obtained from J.W. Miller, part no. RFC-50.

The birdcage coil 60 and the coil interface 100 are designed so that the two quadrature signal components from this coil element may selectively be combined into a single signal for simultaneous use with the other three coil elements. This provides coverage of the entire volume within the quadrature neurovascular array 50 using a total of four simultaneous data acquisition channels [receivers] from the MRI system. In addition, by combining the two quadrature signal components, a preferred embodiment allows for applications employing a single FAST receiver, where only one of the available phased array receivers has the FAST data acquisition capability.

When the brain or the brain, brain stem, and cervical region of the spinal cord, for example, are to be imaged with the highest possible image signal to noise ratio and uniformity, another mode may be used. Specifically, the coil interface 100 directs the two quadrature components of the MR signal from the tapered birdcage coil element 60 into two separate receivers for optimum results. An advantage of this feature is that it preserves the ability to simultaneously cover the entire region from the aortic arch to the top of the head in one phased array acquisition, enables the use of one high performance receiver channel for complete acquisition of images from the brain, and yet enables the highest degrees of resolution, signal to noise ratio, and uniformity to be obtained from the brain, and associated neurological areas of interest by acquiring the data from the two quadrature modes of the tapered birdcage coil element through two separate receivers.

The coil interface 100 supports distinct imaging functions by automatic selection of the optimum assembly of the array coil elements. As described below, the coil interface 100 may be remotely configured, i.e. the state of one or more PIN diode RF switches may be set, based upon inputs from the MRI system console. Examples of distinct imaging modes that may be supported a coil interface, such as the coil interface shown in Figures 2A and 2B, include: NEUROVASCULAR, HIGH RESOLUTION BRAIN, HIGH SPEED BRAIN, HIGH RESOLUTION BRAIN AND CERVICAL SPINE, CERVICAL SPINE, and VOLUME NECK.

Each of these modes is preferably activated by selecting the appropriate Coil Name from the coil selections on the console of the host MRI system when prescribing the scan. By way of the coil interface 100, the needed coils and the signal combining method are activated for the selected mode, and the unused coil elements are electronically disabled to optimize image quality and minimize artifacts. Each mode has a distinct method of operation as described below.

NEUROVASCULAR Mode

In NEUROVASCULAR mode, all of the coil elements in the phased array neurovascular coil 50 are active, and the birdcage coil 60 operates in quadrature with the two signals combined to drive a single receiver. Specifically, the coil interface 100 includes a combiner circuit, including a switch and a phase shifter, that is set to combine the in-phase, or "I," output and the quadrature, or "Q," output of the birdcage coil 60 before applying the signal to the MRI system preamplifier at port #5. The two posterior spine coils 70 drive a single receiver, such as port #4. The superior anterior neck coil 80 and the inferior anterior neck coil 90 each drive a separate receiver, such as ports #3 and #2, respectively. Thus, in NEUROVASCULAR mode, the coil interface 100 provides a total of four simultaneous data acquisitions, the maximum number of simultaneous data acquisitions that can be handled by the MRI system. Since the coverage volume is large, the signal to noise ratio performance of the head portion of the coverage may be slightly reduced, by the combination of the I and Q outputs of the birdcage coil 60, to allow only one receiver channel to be used to cover the head region.

Figure 3 is a wire model of the phased array neurovascular coil 50 in NEUROVASCULAR mode. As noted above and shown in Figure 3, all elements of the phased array neurovascular coil 50 are activated and the MRI system operates in the phased array mode. The NEUROVASCULAR mode may be used for all types of brain and neck imaging, other than Echo Planar Imaging. The NEUROVASCULAR mode is particularly useful for brain and/or cervical spine localizers, imaging of the cervical spine, imaging of the carotid arteries, and imaging of the aortic arch. The preferred embodiment shown in Figure 3 advantageously provides a field of view of up to 46 cm.

HIGH RESOLUTION BRAIN Mode

In HIGH RESOLUTION BRAIN mode, the two quadrature components of the MR signal from the birdcage coil 60 each drive a separate receiver channel on the MRI system, providing optimum uniformity and signal to noise ratio performance. Specifically, the coil interface 100 couples the I and Q signals from the birdcage coil 60 to separate receiver ports on the MRI system, such as ports 5 and 6, as shown in Figure 2A and the table above. The combiner circuit in the coil interface 100 is electrically disconnected to allow independent reconstruction of the data from the two channels. The posterior cervical spine coils 70 and the anterior neck coils 80 and 90 are electrically disabled to minimize artifacts and undesirable coil interactions. Since the highest possible degree of signal to noise ratio and uniformity are desired, but coverage of the entire volume of the coil is not needed, two separate receivers are used for the birdcage coil 60 MR signal. Techniques for electrically disabling an imaging coil are well known to those skilled in the art.

Figure 4 is a wire model of the phased array neurovascular coil in HIGH RESOLUTION BRAIN imaging mode. As shown in Figure 4, only the quadrature birdcage coil 60 is activated; the cervical spine coils 70 and the anterior neck coils 80 and 90 are electrically disabled. The MRI system operates in phased array mode. The HIGH RESOLUTION BRAIN imaging mode may be used for all types of brain and/or head imaging, other than echo planar imaging, but is especially useful for high resolution studies of the brain. The HIGH RESOLUTION BRAIN imaging mode is also useful for high resolution Circle of Willis imaging. The preferred embodiment shown in Figure 4 provides a field of view of up to 24 cm.

HIGH SPEED BRAIN Mode

The HIGH SPEED BRAIN mode routes the two quadrature modes of the head birdcage resonator 60 through the combiner circuit in the coil interface 100 to produce one signal containing the signal from both quadrature modes. In Figure 2A, the combined signal is provided to the MRI system at port #5. The combined signal drives one channel of the phased array system [preferably Receiver 0 (Receiver selection 1 on LX systems) for the GEMS Signa system] to minimize reconstruction time or to allow the use of a single FAST receiver. All other coil elements are electrically disabled.

Figure 5 is a wire model of the phased array neurovascular coil 50 in HIGH SPEED BRAIN mode. Like Figure 4, only the quadrature birdcage coil 60 is activated; the cervical spine coils 70 and the anterior neck coils 80 and 90 are electrically disabled. The HIGH SPEED BRAIN mode may be used for Echo Planar Imaging and/or vascular or other studies of the brain where decreased acquisition time is desirable. HIGH SPEED BRAIN mode is also useful for imaging the Circle of Willis.

Additional modes of operation for the phased array neurovascular coil 50 may be used by providing the MRI system with the appropriate port masks for the coil interface 100. For example, embodiments of the phased array neurovascular coil 50 may also acquire images from one or more of the following operational modes: HIGH RESOLUTION BRAIN AND CERVICAL SPINE, CERVICAL SPINE and VOLUME NECK. Each of these modes is described in further detail below. For these alternative embodiments, unless otherwise noted, it is assumed that the cervical spine coils 70 are applied separately to the coil interface, rather than being combined at the RF level, and the anterior neck coils 80 and 90 are either combined to provide a single input to the coil interface or replaced by a single anterior neck coil.

HIGH RESOLUTION BRAIN AND CERVICAL SPINE Mode

This mode activates the head and posterior cervical spine coils, and disables the anterior neck coil. This allows focal studies of the brain, brain stem, spinal cord, and cervical spine. The two quadrature components of the MR signal from the birdcage coil 60 each drive a separate receiver channel for optimum uniformity and signal to noise ratio performance. The combiner circuit is electrically disconnected to allow independent reconstruction of the data from the two channels. The two posterior cervical spine coils 70 also each drive a separate receiver channel.

CERVICAL SPINE Mode

In CERVICAL SPINE mode, the two quadrature components of the MR signal from each of the two posterior cervical spine coil elements 70 each drive a separate receiver channel for optimum uniformity and signal to noise ratio performance. The head coil element 60 and the anterior neck coil 80, 90 are electrically disabled to minimize artifacts and undesirable coil interactions.

VOLUME NECK Mode

This mode disables the tapered birdcage coil covering the head region, and activates the three spine region coils to form a volume acquisition of the neck region. The two quadrature components of the MR signal from each of the two posterior cervical spine coil elements 70 and the anterior neck coil 80, 90 each drive a separate receiver channel for optimum uniformity and signal to noise ratio performance. In one embodiment, the MR signals from the two posterior cervical spine coils 70 are combined at the RF level and applied as a single input to the coil interface 100, along with the two MR signals from the anterior neck coils 80 and 90. For embodiments in which the anterior neck coils 80 and 90 are combined at the RF level, the cervical spine coils 70 are combined at the RF level, or only a single anterior neck coil is used, the acquisition uses an unoccupied channel for the fourth channel [GEMS Signa does not directly support a three coil acquisition; Phased Array Data sets must be from one, two, or four receivers].

As noted above, selection of the modes is made in the coil interface 100 unit by the use of PIN diode RF switches; the switches either direct the two quadrature signals from the two modes of the birdcage coil element 60 to two separate MR receivers, or combine them with a relative phase difference of 90° and direct them to a single receiver. Determination of which mode to support is made via detection of the bias pattern of the ports in the host GEMS Signa MRI system. As will be apparent to those skilled in the art, the electrical length of the path of the various MR signals through the coil interface 100 should be compensated to ensure that the MR signals may be properly combined by the MRI system. For example, the electrical lengths of the paths through the coil interface 100 may be adjusted to be an integer multiple of half wavelengths.

In view of the wide variety of embodiments to which the principles of the present invention can be applied, it should be understood that the illustrated embodiments are exemplary only, and should not be taken as limiting the scope of the present invention. For example, the steps of the design method may be taken in sequences other than those described, and more or fewer elements may be used than are described. In addition, although reference is made herein to



Country	Year	Value	Unit
Algeria	1970	1.00	1000
Algeria	1971	1.00	1000
Algeria	1972	1.00	1000
Algeria	1973	1.00	1000
Algeria	1974	1.00	1000
Algeria	1975	1.00	1000
Algeria	1976	1.00	1000
Algeria	1977	1.00	1000
Algeria	1978	1.00	1000
Algeria	1979	1.00	1000
Algeria	1980	1.00	1000
Algeria	1981	1.00	1000
Algeria	1982	1.00	1000
Algeria	1983	1.00	1000
Algeria	1984	1.00	1000
Algeria	1985	1.00	1000
Algeria	1986	1.00	1000
Algeria	1987	1.00	1000
Algeria	1988	1.00	1000
Algeria	1989	1.00	1000
Algeria	1990	1.00	1000
Algeria	1991	1.00	1000
Algeria	1992	1.00	1000
Algeria	1993	1.00	1000
Algeria	1994	1.00	1000
Algeria	1995	1.00	1000
Algeria	1996	1.00	1000
Algeria	1997	1.00	1000
Algeria	1998	1.00	1000
Algeria	1999	1.00	1000
Algeria	2000	1.00	1000
Algeria	2001	1.00	1000
Algeria	2002	1.00	1000
Algeria	2003	1.00	1000
Algeria	2004	1.00	1000
Algeria	2005	1.00	1000
Algeria	2006	1.00	1000
Algeria	2007	1.00	1000
Algeria	2008	1.00	1000
Algeria	2009	1.00	1000
Algeria	2010	1.00	1000
Algeria	2011	1.00	1000
Algeria	2012	1.00	1000
Algeria	2013	1.00	1000
Algeria	2014	1.00	1000
Algeria	2015	1.00	1000
Algeria	2016	1.00	1000
Algeria	2017	1.00	1000
Algeria	2018	1.00	1000
Algeria	2019	1.00	1000
Algeria	2020	1.00	1000
Algeria	2021	1.00	1000
Algeria	2022	1.00	1000
Algeria	2023	1.00	1000
Algeria	2024	1.00	1000
Algeria	2025	1.00	1000
Algeria	2026	1.00	1000
Algeria	2027	1.00	1000
Algeria	2028	1.00	1000
Algeria	2029	1.00	1000
Algeria	2030	1.00	1000
Algeria	2031	1.00	1000
Algeria	2032	1.00	1000
Algeria	2033	1.00	1000
Algeria	2034	1.00	1000
Algeria	2035	1.00	1000
Algeria	2036	1.00	1000
Algeria	2037	1.00	1000
Algeria	2038	1.00	1000
Algeria	2039	1.00	1000
Algeria	2040	1.00	1000
Algeria	2041	1.00	1000
Algeria	2042	1.00	1000
Algeria	2043	1.00	1000
Algeria	2044	1.00	1000
Algeria	2045	1.00	1000
Algeria	2046	1.00	1000
Algeria	2047	1.00	1000
Algeria	2048	1.00	1000
Algeria	2049	1.00	1000
Algeria	2050	1.00	1000
Algeria	2051	1.00	1000
Algeria	2052	1.00	1000
Algeria	2053	1.00	1000
Algeria	2054	1.00	1000
Algeria	2055	1.00	1000
Algeria	2056	1.00	1000
Algeria	2057	1.00	1000